Compact & High performance

Compact size meeting UL489 480V requirements

& same dimensions as ELCB

Rated voltage 480V

**Technical innovation** 

**Ecology** 

Recycling

(125 to 800AF)

Arc and gas flow control technology

**Advanced environmental technology** 

The G-TWIN Series is designed to lower

• For easier recycling, all major parts are marked with the

Conforming to the RoHS Directive

environmental impact.


names of the materials used.

Conforming to the RoHS Directive

· Lead-free (Pb-free) solder is used.

Free of hexavalent chromium (Cr<sup>6+</sup>-free)

Effect of "ablation breaking technology"



Rated voltage 480V

Arcing prevention at the bottom of mo

Magnetic yoke arrangemen

Cadmium-free contact material

force of the moving contact at initiation of contact opening

30%

Increased arc voltage and high

Suppression of internal pressure rise

by adjusting the narrow slit width

Stationary

contact

### **Usefulness** Leading the way in user-friendliness



Undervoltage

trip device

Shunt trip device

MCCB

800



### Innovating Energy Technology



# **FUJI Molded Case Circuit Breakers**







62D9-E-0221a

### Fuji Electric FA Components & Systems Co., Ltd.

## **FUJI MCCB and ELCB GLOBAL TWIN**

The Twin Breakers have advanced to an entirely new stage.

MCCB

### Conforming to IEC & local Standards

Conforming to certifications and standards in major world markets Expanded frame sizes in G-TWIN Global Series

#### **Compact & High performance**

Compact models with unified dimensions meeting UL489 480V and IEC 440V requirements

#### **Ecology**

Lower environmental impact Advanced green engineering and energysaving support Conforaming to the RoHS Directive

#### Usefulness

Leading the way in user-friendliness

**G-TWIN** Standard series











#### the first time in the world. The Twin Breaker Series was highly evaluated and gained strong support, and the concept of Twin Breakers was established as Japan's de facto standards for MCCBs and ELCBs.

In 1992, Fuji Electric released the Super Twin Breaker Series, which enabled user installation of internal accessories for the first time in Japan.

In 1995, Fuji Electric released the Super 60 Series and advanced modularization via uniform external dimensions. In 2001, Fuji Electric launched the  $\alpha$ -Twin Series to further advance the miniaturization and modularization of economic types with 100A frame or less as Japan's first multi-standard circuit breakers satisfying domestic and international standards. Since then, Fuji Electric has been making further product improvements by predicting market trends.

Fuji Electric launched the Twin Breaker Series to world markets in 1990, in which molded case circuit

breaker (MCCB) and earth leakage circuit breaker (ELCB) types were unified in external dimensions for

At the end of 2004, the Japanese Industrial Standards (JIS) were aligned with the IEC standards, and the globalization in this field has been further accelerated.

Based on the Twin Breaker Series, Fuji Electric has expanded the range of its products conforming to and approved by international standards for global markets, always advanced the innovative development of fundamental technologies in response to the market demand, and developed the G-TWIN Series of



1992 Super TWIN 1995 Super 60 2001 α-TWIN **2006 G-TWIN** 

Fuji Electric FA Components & Systems Co., Ltd.

5-7, Nihonbashi Odemma-cho, Chuo-ku, Tokyo 103-0011, Japan URL http://www.fujielectric.co.jp/fcs/eng/

2018-4 PDF FOLS 62D9-E-0221a Information in this catalog is subject to change without notice.



## **FUJI Molded Case Circuit Breakers**

G-TWIN IEC/EN60947-2,	<b>Series</b> GB14048.2, JISC	C8201-2-1	32A	CCC	BW32SAG	50AF BW50AAG	BW50EAG	BW50	0SAG	BW50ZSG	BW50RA		63AF  BW63EAG	BW63SAG	BW63ZS0	BW63RAG		00AF W100AAG		AG AG	1			BW125RAG		BW125HAG			250JAG		BW250RA	ıG	BW250HAG
Pole			2	3	2 3	2 3	2 3	2	3	3	2	3	2 3	2 3	3	2 3	3 3		2	3	2	3	4* <sup>3</sup>	2 3 4	4	3	2 ;	3 2	3	4* <sup>3</sup>	2	3 4	3
Rated current	Rated current In [A]			] 3, 5, 10, 15, 20, 30, (32)*3		5, 10, 15, 20, 30, (32)*3 40, 50 10, 15, 20, (32)*3 40, 50				), 30, 50	60, (63)* <sup>3</sup> 60, (63)* <sup>3</sup> 50, 75, 100 100					50, 60, (63)*3 75, 15, 20, 30, 40, 50, 60, 75, 100, 125						125, 150, 160, 175, 200, 225, 250											
Rated impulse wi	ithstand voltage	Uimp [	kV] 6			6							6						6				6	6									
Isolation complia	nt		Approved			Approved							Approved Approved							Approved				Approved	Approved								
Rated insulation	voltage Ui [	[V] AC	AC 500		690	500	690	690		690 690			690 690		690	690 690		500 690		690					690								
			_		250* <sup>1</sup>	- 250* <sup>1</sup> 250*1 -			250*1		250* <sup>1</sup>						250* <sup>1</sup>	250 –					_	250 –				_					
Rated frequency	Rated frequency [Hz]			50-60		50-60							50-60 50-60 50-60				5	0-60	50-60		50-60					50-60							
Rated breaking	CNS14816-2 AC IEC60947-2 EN60947-2 JIS8201-2-1 Icu/Ics	690\	'  -		_	_	_	_		_	_		_	_		_			_		_			_		_	_	_			_		_
capacity [kA]		500V	'  -		1.5/1	_	1.5/1	5/3		_	7.5/4		1.5/1	5/3	_	7.5/4			7.5/4		5/3	15/8		36/18		15/4	10/5	15/8			36/18		15/4
,		440V	1.5/1		2.5/2	1.5/1	2.5/2	7.5/4		7.5/4	10/5		2.5/2	7.5/4	7.5/4	10/5	-		10/5		30/15			50/25		65/17	18/9	30/1	ذ		50/25		65/17
		415V			2.5/2	1.5/1	2.5/2	7.5/4		7.5/4	10/5		2.5/2	7.5/4	7.5/4	10/5	1	.5/1	10/5		30/15			50/25		65/17	18/9	30/1	5		50/25		65/17
		400V																															
		240\			5/3	2.5/2	5/3	10/5		15/8	25/13		5/3	10/5	15/8	25/13	5	/3	25/13		50/25			100/50		125/63	36/18	50/2	5		100/50		125/63
		230\	'																														
	DC	250\	'  -		2.5/2*1	_	2.5/2*1	5/3*1		-	5/3* <sup>1</sup>		2.5/2*1	5/3* <sup>1</sup>	_	5/3*1	-		5/3*1		15/8			40/20		40/20	10/5	20/1	)		30/15		40/20
	GB14048.2 AC				2.5/2	1.5/1	2.5/2	7.5/4		-	10/5		2.5/2	7.5/4	-	10/5	1	.5/1	10/5		30/15			50/25		_	18/9	30/1	<u>ن</u>		50/25		_
	lcu/lcs	230\			5/3	2.5/2	5/3	10/5		-	25/13		5/3	10/5	_	25/13	5	/3	25/13		50/25			100/50		_	36/18	50/2	5		100/50		_
	NEMA AC		'/Y 1.5* <sup>2</sup>		2.5*2	1.5*2	2.5*2	7.5* <sup>2</sup>		7.5* <sup>2</sup>	10*2		2.5*2	7.5*2	7.5*2	10*2			10*2		30		30*2	50		_	18	30		30*2	50		_
	AB1	240\	2.5*2		5* <sup>2</sup>	2.5*2	5*2	10*2		15* <sup>2</sup>	25*2		5* <sup>2</sup>	10*2	15* <sup>2</sup>	25* <sup>2</sup>	5	*2	25* <sup>2</sup>		50		50* <sup>2</sup>	100		_	36	50		50* <sup>2</sup>	100		-
Dimensions	L	m] a	50	75	50 75	50 75	50 75	50	75	75	50	75	50 75	50 75	75	50 7	75 7	5	50	75	60	90	120	90 90	120	90	105	105	105	140	105	105 140	0 105
- a -	-d→ - C -	b	100		100	100	100	100		100	100		100	100	100	100	1	00	100		155			155			165	165			165		
	4	С	60		60	60	60	60		60	60		60	60	60	60	6	0	60		68			68			68	68			68		
	<u> </u>	d	84		84	84	84	84		84	84		84	84	84	84	8	4	84		95			95			95	95			95		
Mass			kg] 0.4	0.5	0.4 0.5	0.4 0.5	0.4 0.5	0.4	0.5	0.5	0.4	0.5	0.4 0.6	0.4 0.6	0.6	0.4	0.6	.6	0.4	0.6	0.8	1.2	1.6	1.0 1.2	1.6	1.2	1.4	1.6 1.4	1.6	2.2	1.4	1.6 2.2	1.6
Tripping device			Hydra	ulic-magnetic																	Thermal-	magnetic											

IEC/EN60947-2	<b>  series</b> 2, GB14048.2, J	ISC82		- 342		G								630AF	C	72			800AF	C			
Туре				BW400E		BW4009		BW400F			BW400			BW630EAG	BW630F		BW630	_	BW800EAG	BW800F		BW800F	
Pole				2		2	3	2	3	4*3	2	3	4	3	3	4*3	3	4	3	3	4*3	3	4
Rated current			In [A]	250, 300	, 350, 400									500, 600, 630					700, 800				
Rated impulse		ge L	Jimp [kV]	8										8	8								
Isolation compli				Approved															Approved				
Rated insulation	n voltage	Ui [V]		690										690					690				
			DC	250										250					250				
Rated frequenc	у		[Hz]	50-60			_			_				50-60					50-60				
Rated breaking	CNS14816-2	AC	690V	_		10/5		15/8			15/8			_	15/8		15/8		_	15/8		15/8	
capacity [kA]	EN60947-2		500V	18/9		22/11		36/18			42/21			22/11	36/18		42/21		22/11	36/18		42/21	
	JIS8201-2-1		440V	30/15		36/18		50/25			70/35			36/18	50/25		70/35		36/18	50/25		70/35	
	lcu/lcs		415V																				
			400V																				
			380V																				
			240V	50/25		85/43		100/50			125/63			50/25	100/50		125/63		50/25	100/50		125/63	
			230V																				
		DC	250V	10/5		20/10		30/15			40/20			20/10	40/20		40/20		20/10	40/20		40/20	
	GB14048.2	AC	400V	30/15		36/18		50/25			70/35			30/15	50/25		70/35		36/18	50/25		70/35	
	lcu/lcs		230V	50/25		85/43		100/50			125/63			36/18	100/50		125/63		50/25	100/50		125/63	
	NEMA	AC	480V/Y	30		36		50		50* <sup>2</sup>	70			36	50	50*2	70		36	50	50* <sup>2</sup>	70	
	AB1*2		240V	50		85		100		100*2	125			85	100	100*2	125		85	100	100*2	125	
Dimensions		[mm]	а	140		140		140	140	185	140	140	185	210	210	280	210	280	210	210	280	210	280
<b>-</b> a →			b	257		257		257			257	1	1	275	275		275	1	275	275		275	
				103		103		103			103			103	103		103		103	103		103	
	d d					146		146			146			146	146		146		146	146		146	
Mass			[kg]	4.3	5.1	4.3	5.1	4.3	5.1	6.8	4.3	5.1	6.8	7.8	7.8	10.3	7.8	10.3	8.3	8.3	11	8.3	11
	Fripping device						1				1					1			1				

H series,	S seri	es		225AF	400AF	600AF	800AF	1000AF	1200AF	1600AF		
Туре				H203R	H403R	H603R	H803R	S1003	S1203	SE1603		
Pole				3	3	3	3	3	3	3		
Rated current			In [A]	40, 50, 60, 75, 100, 125, 150, 175, 200, 225	250, 300, 350, 400	500, 600	700, 800	1000	1200	Selectable* <sup>5</sup> 1000- 1200- 1400- 1600		
Rated insu lation vo	oltage	Ui [v]	AC	660	690			660*4		660*4		
			DC	250	250			_		_		
Rated frequency			[Hz]	50-60	50-60		50 or 60* <sup>4</sup>					
Rated breaking IE	C60947-2	AC	660V	_	_	_	_	30	30	35		
	ISC8201-2-1 cu/lcs		600V	35	_	_	_	30	30	65		
. IE	EC157-1*6		500V	42	85/43	85/43	85/43	35	35	65		
			440V	85	125/63	125/63	125/63	50	50	85		
			415V									
			400V	100				50	50	85		
			380V									
			230V	125	125/63	125/63	125/63	85	85	130		
		DC	250V	40	40/20	40/20	40/20	_	_			
Dimensions		[mm]	а	105	140	210	210	210	210	210		
- a →	-d→ - c -		b	165	257	275	275	400	400	406		
	4		С	99	103	103	103	105	105	140		
			d	127	146	146	146	158	158	193		
Mass			[kg]		5	9	10	21	21	34		
Tripping device				Thermal-magnetic			Thermal-adjastable r	Solid state				

<sup>\*1</sup> Specify DC only when ordering circuit breakers for DC circuit.
\*2 The rating "NEMA AB-1" does not appear on the nameplates of the BW32 to BW100, BW125JAG-4P to BW250JAG-4P, and BW400RAG-4P to BW800RAG-4P.
\*3 Contact FUJI.

<sup>\*4</sup> Specify frequency when using in AC circuits (50Hz or 60Hz)
\*5 Breakers with 1000A or 1200A fixed rated current can be made if specified.
\*6 Applies to the H203R, S1003, S1203, and SE1603.